TITLE OF THE INVENTION

CALCULATING METHOD, VERIFICATION METHOD, VERIFICATION

PROGRAM AND VERIFICATION SYSTEM FOR EDGE DEVIATION

QUANTITY, AND SEMICONDUCTOR DEVICE MANUFACTURING METHOD

CROSS-REFERENCE TO RELATED APPLICATIONS

This application is based upon and claims

the benefit of priority from prior Japanese Patent

Application No. 2003-074821, filed March 19, 2003,

the entire contents of which are incorporated herein

by reference.

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a technique

for manufacturing an exposure mask for use in a light

or X-ray exposure method, and more particularly, the

present invention relates to a calculation method,

a verification method, a verification program,

a verification system, and a semiconductor device

manufacturing method, for an edge deviation quantity of

a finish pattern from a desired pattern in order to

obtain a fine pattern.

2. Description of the Related Art

Advancement of a semiconductor manufacturing

technique in recent years is very remarkable, and a

semiconductor device such as LSI whose size is 0.18 μm

in minimum design rule is mass-produced. Such a fine

LSI is achieved by remarkable advance of a fine pattern

forming techniques such as a mask process technique,
a photolithography technique, and an etching technique.

In an age in which a pattern size is large, an LSI
pattern to be formed on a wafer is depicted as a design
pattern as is; a mask pattern which is faithful to
the design pattern is produced; the mask pattern is
transferred onto the wafer by means of a projection
optical system; and a target layer is etched, whereby a
pattern which is almost identical to the design pattern
can be formed on the wafer. However, with advancement
of fine patterning, it becomes difficult to faithfully
form a pattern in each process. Thus, there occurs
a problem that the finish pattern is not provided as
the desired pattern.

With respect to how patterns are called, such
patterns are discriminated from one another as follows.
A pattern desired as an LSI in view of device features,
wiring characteristics or the like is referred to as
a "desired pattern", a pattern obtained by designing
a pattern as close to the desired pattern as possible
is referred to as a "design pattern", and a pattern
to be formed on a wafer, which is predicted from the
design pattern, is referred to as a "finish pattern".

In particular, in lithography and an etching
process which are the most important to achieve fine
processing, another pattern layout environment
allocated in a peripheral region of a region for

forming a pattern is greatly influenced on dimensional precision of the pattern. As a technique for reducing the influence, there has been reported a correction technique such as a technique for Optical Proximity

5 Correction (hereinafter, simply referred to as OPC) or a technique for Process Proximity Correction (hereinafter, simply referred to as PPC) in which an auxiliary pattern is added in advance in a design pattern such that a finish pattern is close to the

10 desired pattern.

However, with complication of the OPC and PPC techniques in recent years, a pattern produced by a device designer and a mask pattern for use during exposure are greatly different from each other, and

15 thus, a finish pattern to be formed on a wafer cannot be easily predicted. Therefore, in the case where a desired pattern cannot be obtained as a result of simulation after the finish pattern has been predicted by using an OPC tool and a lithography simulator,

20 a design technique is employed for correcting a design pattern. In such a design technique, it is required that an edge deviation quantity indicating a deviation between a design pattern and a finish pattern is calculated within a short period of time.

25 There has been proposed that the edge deviation quantity is calculated by computing a light beam intensity using a Hopkins's Formula (US Patent

No. 6470489 (page 20). A conventional method of calculating an edge deviation quantity based on the Hopkins Formula will be described with reference to FIGS. 13 to 15.

FIG. 13 schematically shows a desired pattern 41 and a design pattern 42 with respect to a method of calculating an edge deviation quantity, and also schematically shows a light beam intensity obtained from the design pattern 42. These patterns are depicted to correspond to a position coordinate shown in FIG. 13. FIG. 14 is a flow chart showing an outline of procedures for obtaining an edge deviation quantity. FIG. 15 is a flow chart showing calculation procedures in the Hopkins Formula in steps S54 and S55.

First, in designing an LSI or the like, the desired pattern 41 required to ensure device characteristics and the design pattern 42 to achieve the desired pattern 41 are produced (step S51). The design pattern 42 is not applied with OPC or the like.

Next, an exposure reference light beam intensity (Ith) for forming the design pattern 42 on a wafer is set (step S52).

Then, in order to make a comparison of a finish pattern obtained by calculation based on the design pattern 42 with the desired pattern 41, a plurality of evaluation points, for example, two evaluation points, i.e., an evaluation point 51 indicating an edge

position of the desired pattern 41 and an evaluation

point 52 in the vicinity of the evaluation point 51,

are set on a light beam intensity characteristic curve

(step S53).

5   Then, a light beam intensity $I(t_5)$ in the

evaluation point 51 (position coordinate t_5) of an edge

position of the desired pattern 41 is calculated from

the Hopkins Formula described later (step S54).

          Next, a light beam intensity $I(t_6)$ in a position

10   coordinate t_6 of the evaluation point 52 which is

slightly displaced from the position coordinate t_5 is

calculated from the Hopkins Formula (step S55).

          Here, in the above steps S54 and S55, a partial

coherent image forming Formula of Hoplkins for use in

15   calculation of a light beam intensity is expressed as

follows.

$$I(t) = \int\int_{-\infty}^{\infty} TCC(\omega, \omega') \times M(\omega) \times M(\omega')* \times \exp(i(\omega - \omega')t)d\omega d\omega'$$

20   In Formula (1), TCC denotes a Transmission Cross

Coefficient; $I(t)$ denotes a light beam intensity in

a position coordinate "t"; M denotes Foulier transform

of a mask complex transmission rate distribution in

a frequency plane; M* denotes a complex conjugate of

25   Foulier transform of the mask complex transmission

distribution in the frequency plane; "i" denotes

an imaginary unit; and ω and ω' denote angular

frequencies.

Now, calculation procedures of Formula (1) will be described with reference to a flow chart of FIG. 15.

First, calculation of $TCC(\omega, \omega')$ is carried out (step S61).

Subsequently, $M(\omega)$ Foulier transform of complex amplitude transmission distribution of the design pattern is carried out, and $M(\omega')$ is determined (step S62).

Next, a product of the calculated results in steps S61 and S62, which expressed by $TCC(\omega, \omega') \times M(\omega) \times M(\omega')$, is calculated (step S63).

Then, a product of the formula in step S63 and exp $(i(\omega - \omega')t)$ which is reverse Foulier transform in step S63 is integrated with respect to ω, ω' (step S64).

As has been described above, by the above-described Hopkins Formula of Formula (1), light beam intensity $I(t_5)$, $I(t_6)$ of the position coordinate t_5, t_6 of the evaluation points 51 and 52 are calculated, and a Formula of a straight line 53 connecting the light beam intensity $I(t_5)$, $I(t_6)$ of the position coordinate t_5, t_6 of these evaluation points 51 and 52 is calculated (step S56).

Next, from this straight line 53, a position coordinate t_7 of an intersection 54 at which the light beam intensity becomes a reference light beam intensity (Ith) is calculated (step S57).

Then, a difference between the position coordinate

t_5 and the position coordinate t_7 is calculated, and this difference is defined as an edge deviation quantity 56 (step S58).

In this manner, it is quantitatively determined how large the finish pattern calculated from the design pattern 42 is deviated from the desired pattern 41.

In the above-described conventional method of calculating an edge deviation quantity, the light beam intensities in the position coordinates t_5 and t_6 of the two evaluation points 51 and 52 are calculated by the above-described Hopkins Formula. In this case, it is required to calculate reverse Foulier transform of an angular frequency distribution at each of the position coordinates. In particular, calculation of a trigonometric function $(\cos(\omega - \omega')t - i\sin(\omega - \omega')t)$ expanding a portion of $\exp(i(\omega - \omega')t)$ on which a great calculation load is applied is carried out two times. Thus, there has been a problem that much time is required for calculation of the trigonometric function, and an edge deviation quantity cannot be calculated with high precision for a short period of time.

BRIEF SUMMARY OF THE INVENTION

According to an aspect of the present invention, there is provided an edge deviation calculation method in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of

a light beam intensity, and a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, the calculation method comprising:

5   setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the finish pattern with the desired pattern;

calculating a light beam intensity at the

10   evaluation point;

calculating a differentiation value of the light beam intensity at the evaluation point;

calculating an intersection of the differentiation value with the reference light beam intensity; and

15   calculating a difference between the intersection and the evaluation point,

wherein the difference is defined as an edge deviation quantity of the finish pattern from the desired pattern.

20   According to another aspect of the present invention, there is provided an edge deviation calculation method in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a

25   calculation of a light beam intensity, and a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired

pattern is calculated, the calculation method comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the finish pattern with the desired pattern;

calculating a light beam intensity at the evaluation point;

calculating a differentiation value of the light beam intensity at the evaluation point; and

dividing a difference between the light beam intensity at the evaluation point and the reference light beam intensity by the differentiation value,

wherein a result of the division is defined as an edge deviation quantity of the finish pattern from the desired pattern.

According to a further aspect of the present invention, there is provided an edge deviation quantity verification method in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, and it is determined whether or not the design pattern is to be corrected based on a result of the calculation of the deviation quantity,

the verification method comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the finish pattern with the desired pattern;

calculating a light beam intensity at the evaluation point;

calculating a differentiation value of the light beam intensity at the evaluation point;

calculating an intersection of the differentiation value with the reference light beam intensity;

calculating a difference between the intersection and the evaluation point, and define the calculated difference as an edge deviation quantity of the finish pattern from the desired pattern; and

verifying the edge deviation quantity,

wherein, in the case where the edge deviation quantity exceeds an allowable range, the design pattern is corrected based on the deviation quantity.

According to a further aspect of the present invention, there is provided an edge deviation quantity verification method in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired

pattern is calculated, and it is determined whether or
not the design pattern is to be corrected based on
a result of the calculation of the deviation quantity,
the verification method comprising:

5   setting a reference light beam intensity for
setting the desired pattern on a wafer;

setting an evaluation point for comparison of the
finish pattern with the desired pattern;

calculating a light beam intensity at the

10   evaluation point;

calculating a differentiation value of the light
beam intensity at the evaluation point;

dividing a difference between the light beam
intensity at the evaluation point and the reference

15   light beam intensity by the differentiation value, and
defining a result of the division as an edge deviation
quantity; and

verifying the edge deviation quantity,

wherein, in the case where the edge deviation

20   quantity exceeds an allowable range, the design pattern
is corrected based on the deviation quantity.

According to a further aspect of the present
invention, there is provided an edge deviation quantity
verification program in which a desired pattern is

25   compared with a finish pattern to be formed on a wafer,
which is predicted from a design pattern, based on
a calculation of a light beam intensity, a deviation

quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, and it is verified whether or not the design pattern is to be corrected based on

5   a result of the calculation of the deviation quantity, the verification program comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the

10   finish pattern with the desired pattern;

calculating a light beam intensity at the evaluation point;

calculating a differentiation value of the light beam intensity at the evaluation point;

15   calculating an intersection of the differentiation value with the reference light beam intensity;

calculating a difference between the intersection and the evaluation point, and define the calculated difference as an edge deviation quantity of the finish

20   pattern from the desired pattern; and

verifying the edge deviation quantity,

wherein, in the case where the edge deviation quantity exceeds an allowable range as a result of the verification, the design pattern is corrected based on

25   the deviation quantity.

According to a further aspect of the present invention, there is provided an edge deviation quantity

verification program in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation

5   quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, and it is verified whether or not the design pattern is to be corrected based on a result of the calculation of the deviation quantity,

10   the verification program comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the finish pattern with the desired pattern;

15   calculating a light beam intensity at the evaluation point;

calculating a differentiation value of the light beam intensity at the evaluation point;

dividing a difference between the light beam

20   intensity at the evaluation point and the reference light beam intensity by the differentiation value, and defining a result of the division as an edge deviation quantity; and

verifying the edge deviation quantity,

25   wherein, in the case where the edge deviation quantity exceeds an allowable range, the design pattern is corrected based on the deviation quantity.

According to a further aspect of the present invention, there is provided an edge position quantity verification system having an input/output circuit, a storage, a computer, a display and a controller,

5   in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation quantity of the finish pattern from the desired pattern at each of

10   edges of the finish pattern and the desired pattern is calculated, and it is verified whether or not the design pattern is to be corrected based on a result of the calculation of the deviation quantity, the verification system comprising:

15   setting a reference light beam intensity for setting the desired pattern on a wafer;

           setting an evaluation point for comparison of the finish pattern with the desired pattern;

           calculating a light beam intensity at the

20   evaluation point;

           calculating a differentiation value of the light beam intensity at the evaluation point;

           calculating an intersection of the differentiation value with the reference light beam intensity;

25   calculating a difference between the intersection and the evaluation point, and define the calculated difference as an edge deviation quantity of the finish

pattern from the desired pattern; and

verifying the edge deviation quantity,

wherein, in the case where the edge deviation quantity exceeds an allowable range as a result of the verification, the design pattern is corrected based on the deviation quantity.

According to a further aspect of the present invention, there is provided an edge position quantity verification system having an input/output circuit, a storage, a computer, a display and a controller, in which a desired pattern is compared with a finish pattern to be formed on a wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, and it is verified whether or not the design pattern is to be corrected based on a result of the calculation of the deviation quantity, the verification system comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of the finish pattern with the desired pattern;

calculating a light beam intensity at the evaluation point;

calculating a differentiation value of the light

beam intensity at the evaluation point;

dividing a difference between the light beam intensity at the evaluation point and the reference light beam intensity by the differentiation value, and defining a result of the division as an edge deviation quantity; and

verifying the edge deviation quantity,

wherein, in the case where the edge deviation quantity exceeds an allowable range, the design pattern is corrected based on the deviation quantity.

According to a further aspect of the present invention, there is provided a semiconductor device manufacturing method in which a desired pattern is compared with a finish pattern to be formed on a semiconductor wafer, which is predicted from a design pattern, based on a calculation of a light beam intensity, a deviation quantity of the finish pattern from the desired pattern at each of edges of the finish pattern and the desired pattern is calculated, it is verified whether or not the design pattern is to be corrected based on a result of the calculation of the deviation quantity, and a semiconductor device is manufactured by using a mask having the design pattern corrected based on the verification, the manufacturing method comprising:

setting a reference light beam intensity for setting the desired pattern on a wafer;

setting an evaluation point for comparison of
the finish pattern with the desired pattern;

calculating a light beam intensity at the
evaluation point;

5 calculating a differentiation value of the light
beam intensity at the evaluation point;

calculating an intersection of the differentiation
value with the reference light beam intensity;

calculating a difference between the intersection
10 and the evaluation point, and define the calculated
difference as an edge deviation quantity of the finish
pattern from the desired pattern;

verifying the edge deviation quantity;

correct the design pattern based on the deviation
15 quantity, in the case where the edge deviation quantity
exceeds an allowable range;

forming a mask having the design pattern corrected
based on the deviation quantity; and

forming a pattern corresponding to the corrected
20 design pattern on a semiconductor wafer by using
the mask to form a semiconductor device on the
semiconductor wafer.

According to a further aspect of the present
invention, there is provided a semiconductor device
25 manufacturing method in which a desired pattern is
compared with a finish pattern to be formed on a
semiconductor wafer, which is predicted from a design

pattern, based on a calculation of a light beam
intensity, a deviation quantity of the finish pattern
from the desired pattern at each of edges of the finish
pattern and the desired pattern is calculated, it is

5   verified whether or not the design pattern is to be
corrected based on a result of the calculation of the
deviation quantity, and a semiconductor device is
manufactured by using a mask having the design pattern
corrected based on the verification, the manufacturing

10   method comprising:

setting a reference light beam intensity for
setting the desired pattern on a wafer;

setting an evaluation point for comparison of the
finish pattern with the desired pattern;

15   calculating a light beam intensity at the
evaluation point;

calculating a differentiation value of the light
beam intensity at the evaluation point;

dividing a difference between the light beam

20   intensity at the evaluation point and the reference
light beam intensity by the differentiation value, and
defining a result of the division as an edge deviation
quantity; and

verifying the edge deviation quantity,

25   correct the design pattern based on the deviation
quantity, in the case where the edge deviation quantity
exceeds an allowable range;

forming a mask having the design pattern corrected based on the deviation quantity; and

forming a pattern corresponding to the corrected design pattern on a semiconductor wafer by using

5   the mask to form a semiconductor device on the semiconductor wafer.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

FIG. 1 is a diagram for explaining a method of calculating and verifying an edge position deviation

10   quantity according to a first embodiment of the present invention;

FIG. 2 is a flow chart showing procedures of calculating and verifying an edge deviation quantity according to the first embodiment of the invention;

15   FIG. 3 is a flow chart showing procedures for calculating and verifying an edge deviation quantity according to a second embodiment of the present invention;

FIG. 4 is a diagram showing a mask having

20   a pattern;

FIG. 5 is a characteristic curve showing an edge deviation from a design data;

FIG. 6 is a characteristic curve showing a difference between edge deviations;

25   FIG. 7 is a diagram showing a mask having a pattern;

FIG. 8 is a characteristic curve showing an edge

deviation from a design data;

FIG. 9 is a characteristic curve showing a difference between edge deviations;

FIG. 10 is a schematic diagram showing a verification system for an edge deviation quantity according to a third embodiment of the present invention;

FIG. 11 is a flow chart showing an outline of a calculation program for an edge deviation quantity according to the third embodiment of the invention;

FIG. 12 is a flow chart showing an outline of another calculation program for an edge deviation quantity according to the third embodiment of the invention;

FIG. 13 is a diagram for explaining a conventional method of calculating an edge deviation quantity;

FIG. 14 is a flow chart showing a conventional procedures for calculating an edge deviation quantity; and

FIG. 15 is a flow chart showing procedures for calculating a partial coherent image forming Formula of Hopkins.

DETAILED DESCRIPTION OF THE INVENTION

Hereinafter, embodiments of the present invention will be described with reference to the accompanying drawings.

(First embodiment)

A calculation method and a verification method for an edge deviation quantity according to a first embodiment of the present invention will be described with reference to FIGS. 1 and 2.

FIG. 1 schematically shows a desired pattern 1 and a design pattern 2 with respect to an edge deviation quantity calculating method. Also, schematically disclosed is in FIG. 1 a light beam intensity curve obtained from the design pattern 2. The desired pattern 1 and design pattern 2 and the light beam intensity curve are depicted to correspond to a position coordinate shown in FIG. 1. FIG. 2 is a flow chart showing an outline of procedures for obtaining an edge deviation quantity.

First, the desired pattern 1 and the design pattern 2 are formed (step S11). The desired pattern 1 is required to ensure device characteristics in designing an LSI or the like, and the design pattern 2 is required to achieve the desired pattern 1. The design pattern 2 is not corrected by the OPC or the like.

Next, a reference light beam intensity (Ith) for forming the design pattern 2 on a wafer, for example, a semiconductor wafer, is set in relation to an etching process in a later manufacturing step (step S12).

Then, an evaluation point 11 is set at an edge

position of the desired pattern 1 for comparison of
a predicted finish pattern with the desired pattern 1
(step S13).

Then, a light beam intensity $I(t_1)$ in the position
coordinate t_1 of the evaluation point 11 of the desired
pattern 1 is calculated from the above-described
Formula (1) of Hopkins (step S14).

Next, a differentiation value $I'(t_1)$ of the light
beam intensity $I(t_1)$ in the position coordinate t_1 of
the evaluation point 11 is calculated by the formula
(2) below (step S15).

$$I^n(t) = \int \int_{-\infty}^{\infty} TCC(\omega, \omega') \times M(\omega) \times M(\omega') \times \left(i(\omega - \omega')\right)^n$$
$$\times \exp\left(i(\omega - \omega')t\right) d\omega d\omega'$$

In calculation using Formula (2), a portion of
$\exp(i(\omega - \omega')t)$ at which a large calculation load is
applied refers to a calculation result produced when
the light beam intensity $I(t_1)$ is obtained in step S14.

Then, a position coordinate t_2 of an intersection
14 at which the light beam intensity becomes the
reference light beam intensity Ith is calculated from
a straight light 13 denoting a differentiation value in
the position coordinate t_1 (step S16).

Next, a difference between the position coordinate
t_1 and the position coordinate t_2 is calculated, and
this difference is defined as an edge deviation
quantity 16 (step S17).

In this manner, it is quantitatively determined

how large an edge position of the finish pattern is
deviated from the desired pattern 1.

Then, a calculation result of the edge deviation
quantity is verified. Based on the verification

5   result, in a case where the edge position of the finish
pattern is deviated over the allowable range specified
at a device design stage from that of the desired
pattern, the design pattern 2 is corrected by OPC, PPC,
or the like. Then, the step of calculating the edge

10   deviation quantity described above is again carried
out for the corrected design pattern. In this manner,
the design pattern is corrected such that the edge
deviation quantity between the desired pattern 1 and
the finish pattern is within the allowable range

15   specified at the device design.

According to the first embodiment of the present
invention described above, in a method of calculating a
inclination of light beam intensity in the vicinity of
a position coordinate of a desired pattern, Formula (1)

20   is calculated with respect to the position coordinate
t_1 of an evaluation point of such a desired pattern.
Next, the above inclination is calculated from a
differentiation value of light beam intensity in the
position coordinate t_1. Moreover, in calculation of

25   the differentiation value, a portion of $\exp(i(\omega - \omega')t)$
at which a large calculation load is applied refers
to the calculation result having been produced by

calculating Formula (1) in the preceding step 14, and the calculation can be carried out without requiring new calculation associated with $\exp(i(\omega - \omega')t)$. Thus, an edge deviation quantity can be calculated in a short

5   period of time.

     Next, calculation times were compared in a case of calculating a trigonometric function as in the prior art and in a case of referring to a calculation result attained at a preceding step as in the

10   present embodiment. Here, comparison was made by using a method for calculating $\sin(\omega - \omega')t$ in Formula $(\exp(i(\omega - \omega')t) = \cos(\omega - \omega')t - i\sin(\omega - \omega')t)$ as a trigonometric function.

     A time required for making a calculation of

15    $\sin(\omega - \omega')t$ by 10,000,000 times was about 6 seconds. On the other hand, a time required for referring to the previously calculated $\sin(\omega - \omega')t$ by 10,000,000 times was about 0.6 seconds. That is, a rate of these two calculation times is 10 : 1. The rate of 10 : 1 is

20   also almost the same in the calculation of $\cos(\omega - \omega')t$, and further, this tendency is also almost the same in calculation of $\exp(i(\omega - \omega')t)$ in which addition and subtraction are added. In addition, it was verified that a rate of calculation times is almost

25   the same even in actually calculating Formula (1) of light beam intensity.

     Namely, assuming that a time required for

calculating light beam intensity of two evaluation
points is 2, a time required for calculating light beam
intensity at one evaluation point and a differentiation
value at the evaluation point is about 1.1. Thus,
according to the present embodiment, a time required
for calculating light beam intensity is reduced to
about 1/2 of the conventional calculation time. This
calculation time can be further reduced if computer
performance is improved and the calculation method is
more sophisticated. A rate of calculation times in
a case of obtaining Foulier transform two times and
a case of carrying out Foulier transform one time and
referring to that differentiation coefficient is
maintained to be about 2 : 1 regardless of other
factors.

In the present embodiment, as previously
described, a calculation result of the edge deviation
quantity is verified. Based on the verification
result, in a case where the edge position of the finish
pattern is deviated over the allowable range specified
at a device design stage from that of the desired
pattern, the design pattern 2 is corrected by OPC, PPC,
or the like. Then, the step of calculating the edge
deviation quantity described above is again carried
out for the corrected design pattern. In this manner,
the design pattern is corrected such that the edge
deviation quantity between the desired pattern 1 and

the finish pattern is within the allowable range
specified at the device design.

A mask having the verified and corrected design
pattern is formed and used in manufacturing a semicon-
ductor device. Specifically, a mask having the
verified and corrected design pattern is formed by
using light beam exposure, known lithography, etc.
Using the mask thus formed, the design pattern is
transferred on a semiconductor wafer via the mask.
Thereafter, patterning is carried out to form on the
semiconductor wafer a pattern corresponding to the
corrected design pattern. Masks having various design
patterns in accordance with the semiconductor device to
be formed, are successively used, and the patterning
process is repeated. In this manner, a semiconductor
device is formed on the semiconductor wafer. With the
manufacturing method, since the design patterns of the
masks have been verified and corrected, it is possible
to provide a semiconductor device having high
precision.

(Second embodiment)

Now, a calculation method and a verification
method for an edge deviation quantity according to
a second embodiment of the present invention will be
described with reference to FIG. 3. In FIG. 3, like
steps in the first embodiment are designated by like
reference numerals. A description of like steps is

omitted, and only different steps will be described here.

The present embodiment is different from the above-described first embodiment in that, instead that the position coordinate t_2 of the intersection 14 at which the light beam intensity becomes the reference light beam intensity (Ith) is calculated from the straight line 13 denoting a differentiation value, and a difference between the position coordinate t_2 and the position coordinate t_1 of the evaluation point 11 is defined as an edge deviation quantity, light beam intensity $I(t_1)$ in the position coordinate of the evaluation point 11 and one-story differentiation of the light beam intensity is calculated, and an edge deviation quantity is calculated. That is, an edge deviation quantity ΔCD can be obtained by the formula below.

$$\Delta CD = (I(t) - Ith)/inclination \ldots (3)$$

In this formula, ΔCD represents an edge deviation quantity; $I(t)$ represents a light beam intensity in a position coordinate (t) of an evaluation point; Ith represents a reference light beam intensity; and a inclination represents one-story differentiation of a position coordinate of an evaluation point, respectively.

In the present embodiment, first, as in the above-described first embodiment, step 11 to step 15

are carried out. Then, the edge deviation quantity 16

is calculated by the Formula (3), by using the light

beam intensity $I(t_1)$ in the position coordinate t1 of

the evaluation point 11 calculated in step 14, the

5   reference light beam intensity Ith set in step 12,

and the inclination which is a differentiation value

calculated in step 15 (step S19).

Then, the calculation result of the edge deviation

quantity is verified in the same manner as that in

10   the above-described first embodiment. Based on the

verification result, in a case where the edge position

of the finish pattern is deviated over an allowable

range specified at a device design stage from that of

the desired pattern, the design pattern 2 is corrected

15   by means OPC, PPC or the like. Then, the step of

calculating the edge deviation quantity described above

is again carried out for the corrected design pattern.

In this manner, the design pattern is corrected such

that the position deviation quantity between the

20   desired pattern 1 and the finish pattern is within the

allowable range specified at the device design stage.

In the second embodiment, as in the first

embodiment, a inclination of the light beam intensity

of a desired pattern, which is in the vicinity of

25   the evaluation point in the position coordinate, is

attained by first calculating Formula (1) with respect

to a position coordinate t_1 of an evaluation point of

one desired pattern, and then carrying out calculation
by using a differentiation value of light beam
intensity in this position coordinate t_1. Hence,
the edge deviation quantity can be calculated in

5   a short period of time. Moreover, calculation of
a differentiation value of steps 15 and 16 in the first
embodiment and calculation of a position coordinate t_2
which becomes an intersection 14 between a straight
line 13 denoting this differentiation value and the

10   reference light beam intensity Ith can be omitted,
and thus the calculation time of the edge deviation
quantity is reduced as compared with the first
embodiment.

        Also in this embodiment, a calculation result of

15   the edge deviation quantity is verified. Based on the
verification result, in a case where the edge position
of the finish pattern is deviated over the allowable
range specified at a device design stage from that of
the desired pattern, the design pattern 2 is corrected

20   by OPC, PPC, or the like. Then, the step of
calculating the edge deviation quantity described above
is again carried out for the corrected design pattern.
In this manner, the design pattern is corrected such
that the edge deviation quantity between the desired

25   pattern 1 and the finish pattern is within the
allowable range specified at the device design.

        A mask having the verified and corrected design

pattern is formed and used in manufacturing a
semiconductor device. Specifically, a mask having the
verified and corrected design pattern is formed by
using light beam exposure, known lithography, etc.

5   Using the mask thus formed, the design pattern is
transferred on a semiconductor wafer via the mask.
Thereafter, patterning is carried out to form on the
semiconductor wafer a pattern corresponding to the
corrected design pattern. Masks having various design

10   patterns in accordance with the semiconductor device to
be formed, are successively used, and the patterning
process is repeated. In this manner, a semiconductor
device is formed on the semiconductor wafer. With the
manufacturing method, since the design patterns of the

15   masks have been verified and corrected, it is possible
to provide a semiconductor device having high
precision.

[Example 1]

As an example, by referring to FIGS. 4-6,

20   comparison is made between a deviation quantity
obtained by the method of calculating an edge deviation
quantity according to the present embodiments with
a deviation quantity obtained by a conventional method
for calculating an edge deviation quantity, while

25   specifying a mask pattern used.

As shown in FIG. 4, a dark field mask 21 is
provided as a mask. The dark field mask 21 has a

cutout pattern 22 of a rectangle of 1 μm in a direction

of a long side and 0.09 μm in a direction of a short

side. OPC is applied to the dark field mask 21,

and using the corrected mask, a finish pattern is

5   calculated under a condition of 193 nm in exposure

light wavelength, 0.75 in numerical aperture (NA),

0.85 in coherent factor (σ), 2/3 ring band illumination

(illumination center shield rate), and the reference

exposure quantity Ith = 0.218.

10   Then, a long side pattern edge of a rectangle of

the design data of the mask is divided into equal

intervals along the long side edge. In accordance with

the method according to the present embodiment, the

light beam intensity in the position coordinate of each

15   division point and one-story differentiation of the

light beam intensity are calculated, an edge deviation

quantity (ΔCD1) from the design data is obtained, and

the thus obtained quantity is indicated by a dotted

line in FIG. 5.

20   On the other hand, in accordance with the

conventional method, an edge deviation quantity (ΔCD2)

from the design data is obtained from the light beam

intensity in the position coordinate of the division

point and a light beam intensity in a position

25   coordinate slightly displaced from the position

coordinate, and the thus obtained quantity is indicated

by a broken line in FIG. 5. As shown in FIG. 5, a

curve indicating the edge deviation quantity according
to the method of the present embodiments and a curve
indicting the edge deviation quantity according to
the conventional method almost overlap with each other.
5   A horizontal axis of FIG. 5 indicates a position
coordinate indicated in units of microns, and a
vertical axis indicates an edge deviation quantity
indicated in units of microns.

       FIG. 6 shows a difference ($\Delta CD2 - \Delta CD1$) between
10   the edge deviation quantity ($\Delta CD1$) obtained by the
method of the present embodiment and the edge deviation
quantity ($\Delta CD2$) obtained by the conventional method.
As in FIG. 5, in FIG. 6, a horizontal axis indicates
a position coordinate indicated in units of microns,
15   and a vertical axis indicates a difference in edge
deviation quantity indicated in units of microns.
As shown in FIG. 6, the difference of the two lines
indicating the edge deviations is as small as 0.001 µm
(1 nm) or less, except for a portion corresponding to
20   a pattern corner. Namely, it is found that there
is almost no difference between the edge deviation
quantity obtained by the method of the present
embodiments and the edge deviation quantity obtained by
the conventional method.
25   According to the present embodiments, on the other
hand, the calculation time is about half of that in the
case of using the conventional method.

Therefore, according to the present embodiments, an edge deviation quantity can be calculated with high speed, without decreasing the precision.

[Example 2]

5   As another example of the mask pattern, FIG. 7 shows a bright field mask 31. The bright field mask 31 has a remaining pattern 32 of a rectangle of 1 μm in a direction of a long side and 0.09 μm in a direction of a short side. Similarly to the Example 1 with

10   reference to FIGS. 4-6, a deviation quantity obtained by the method of calculating an edge deviation quantity according to the present embodiment is compared with that of the conventional method, and a comparison result is shown in FIG. 8.

15   That is, a long side pattern edge of a rectangle of the design data of the mask is divided into equal intervals along the long side edge. In accordance with the method according to the present embodiment, the light beam intensity in the position coordinate of each

20   division point and one-story differentiation of the light beam intensity are calculated, an edge deviation quantity (ΔCD1) from the design data is obtained, and the thus obtained quantity is indicated by a dotted line in FIG. 8.

25   On the other hand, in accordance with the conventional method, an edge deviation quantity (ΔCD2) from the design data is obtained from the light beam

intensity in the position coordinate of the division

point and a light beam intensity in a position

coordinate slightly displaced from the position

coordinate, and the thus obtained quantity is indicated

5   by a broken line in FIG. 8. As shown in FIG. 8, a

curve indicating the edge deviation quantity according

to the method of the present embodiments and a curve

indicting the edge deviation quantity according to

the conventional method almost overlap with each other.

10 A horizontal axis of FIG. 8 indicates a position

coordinate indicated in units of microns, and a

vertical axis indicates an edge deviation quantity

indicated in units of microns.

FIG. 9 shows a difference ($\Delta CD2 - \Delta CD1$) between

15 the edge deviation quantity ($\Delta CD1$) obtained by the

method of the present embodiment and the edge deviation

quantity ($\Delta CD2$) obtained by the conventional method.

As shown in FIG. 9, the difference of the two lines

indicating the edge deviations is as small as 0.001 μm

20 (1 nm) or less, except for a portion corresponding to

a pattern corner. Namely, it is found that there is

almost no difference between the edge deviation

quantity obtained by the method of the present

embodiments and the edge deviation quantity obtained

25 by the conventional method. As in FIG. 8, in FIG. 9,

a horizontal axis indicates a position coordinate

indicated in units of microns, and a vertical axis

indicates a difference in edge deviation quantity
indicated in units of microns.

According to the present embodiments, on the
other hand, as previously described, the calculation
time is about half of that in the case of using the
conventional method.

Therefore, according to the present embodiments,
an edge deviation quantity can be calculated with high
speed, without decreasing the precision.

(Third embodiment)

Now, a verification program and a verification
system for an edge deviation quantity according to
a third embodiment of the present invention will be
described with reference to FIGS. 10 and 11.

An edge deviation quantity verification system
100 is shown in FIG. 10.   The system 100 comprises
a computer 101 which makes computing processing and
controls each unit; a storage unit 102 which stores
a computation result, a verification program and the
like; an input unit 103 which inputs each input data
and the like; a storage medium input/output unit 104
which writes a verification program into the storage
unit 102 from a storage medium such as an optical disk
having stored therein a verification program produced
by another computer; and a display unit 105 which
displays input/output information, a computation result
and the like.   A verification program as shown in

FIG. 11 is installed in the edge deviation quantity verification system 100.

The verification program is inputted from the input unit 103 such as a keyboard by an operator, while observing the display unit 105. Alternatively, the verification program produced by another computer is inputted to the computer 101 through the storage medium input/output unit 104 via a storage medium such as an optical disk, and the thus inputted verification program is stored in the storage unit 102.

Then, this verification program can be executed, while observing the display unit 105, by reading out the verification program stored in the storage unit 102 at a computing unit, and inputting required data and the like including an initial condition via the input unit 103. When calculation terminates, the obtained edge deviation quantity or the like is stored in the storage unit 102. The edge deviation quantity or the like stored in the storage unit 102 can be displayed on a screen of the display unit 105, outputted to a printer (not shown), or outputted via the storage medium input/output unit 104 to a storage medium such as a disk or a semiconductor memory.

Here, although an independent verification system has been shown as an example of the verification system, a communication adapter (not shown) for making connection with a data processing network or the like

may be provided.

Now, a program for carrying out calculation of
an edge deviation quantity shown in the above-described
first embodiment is shown in FIG. 11. The program
5   comprises a step S21 of inputting an evaluation layout
of a desired pattern, a design pattern and the like,
an optical condition specified by an exposure device
or the like, a reference light beam intensity specified
by a photo etching process or the like, a position
10   coordinate of a point to be evaluated, and the like;
a step S22 of calculating a light beam intensity of
an evaluation point in accordance with Hopkins Formula
(1); a step S23 of calculating a differentiation value
in accordance with Formula (2) by referring to the EXP
15   portion of Formula (1) calculated during the light beam
intensity calculation in step S22; a step S24 of
calculating an intersection of a differentiation value
with a reference light beam intensity; a step S25 of
calculating a difference between the intersection and
20   the evaluation point, and defining the calculated
difference as an edge deviation quantity; and a step
S26 of outputting the resultant obtained deviation
quantity.

Further, a program for carrying out calculation
25   and verification of an edge deviation quantity,
described in the second embodiment, is shown in
FIG. 12. The program comprises, instead of steps S24

and S25 in the flow chart of FIG. 11, a step S29, as
shown in FIG. 12, of dividing a difference between
a light beam intensity and a reference light beam
intensity by a differentiation value which is a

5   · inclination.

In the above-described program shown in FIGS. 11
and 12, the step or the like of writing a result of
computation processing into a storage unit and reading
out the calculation result are omitted. In addition,

10   in the edge deviation calculation program shown in
FIG. 11, a step of verifying the edge deviation
quantity is added after the step S26. Similarly,
in the edge deviation calculation program shown in
FIG. 12, a step of verifying the edge deviation

15   quantity is added after the step S29.

As described above, in the present embodiments,
calculation can be executed without making an addition
or a change to the conventional edge deviation
verification system in which an edge deviation quantity

20   has been calculated. Moreover, the execution time
can be reduced to about 1/2 as compared with the
conventional calculation of an edge deviation quantity.
Therefore, a work whose quantity is about two times
as much as conventionally can be carried out by the

25   conventional edge deviation quantity verification
system, without making an addition or a change to the
conventional system, thus enabling efficient operation

of the edge deviation quantity verification system.

Also in this embodiment, a calculation result of
the edge deviation quantity is verified. Based on the
verification result, in a case where the edge position

5   of the finish pattern is deviated over the allowable
range specified at a device design stage from that of
the desired pattern, the design pattern 2 is corrected
by OPC, PPC, or the like. Then, the step of
calculating the edge deviation quantity described above

10   is again carried out for the corrected design pattern.
In this manner, the design pattern is corrected such
that the edge deviation quantity between the desired
pattern 1 and the finish pattern is within the
allowable range specified at the device design.

15   A mask having the verified and corrected design
pattern is formed and used in manufacturing a semicon-
ductor device. Specifically, a mask having the
verified and corrected design pattern is formed by
using light beam exposure, known lithography, etc.

20   Using the mask thus formed, the design pattern is
transferred on a semiconductor wafer via the mask.
Thereafter, patterning is carried out to form on the
semiconductor wafer a pattern corresponding to the
corrected design pattern. Masks having various design

25   patterns in accordance with the semiconductor device to
be formed, are successively used, and the patterning
process is repeated. In this manner, a semiconductor

device is formed on the semiconductor wafer. With the manufacturing method, since the design patterns of the masks have been verified and corrected, it is possible to provide a semiconductor device having high

5   precision.

The embodiments of the present invention have been described above. Other various embodiments and modifications may further be provided.

For example, in each of the described embodiments,

10   a product of a coefficient $(i(\omega - \omega'))^n$ attained when a differentiation value of a light beam intensity in the vicinity of an evaluation point has been calculated with an angular frequency distribution component is first calculated, and then the light beam intensity is

15   obtained by carrying out reverse Foulier transform. However, it is possible to produce a plurality of TCCs of differentiated form in advance, and carry out reverse Foulier transform by referring to these TCCs. This method can reduce a calculation load, and it is

20   particularly desirable when a light beam intensity in a wide range is calculated.

In addition, one-story differentiation of a light beam intensity has been used in order to obtain a light beam intensity at a position of an evaluation point.

25   However, when a concept of serial approximation is used, an approximation formula of light beam intensity in the vicinity of a certain evaluation point

(coordinate x = a) can be expressed by a polynomial of
n-story differentiation in the coordinate of x = a.
That is, assuming that the approximation formula is
f(x), when n-story differentiation of light beam
intensity is $f(x)^{(n)}$ (n = 1, 2 ...) and a coefficient
is C_m (m = 0, 1, 2 ...), they can be expressed as shown
in the formula below.

$$f(x) = C_0 f(x = a) + C_1 f^{(1)}(x = a)(X - a) + \ldots$$
$$+ C_{m-1} f(x = a)^{(n-1)}(X - a)^{n-1} + C_m f(x = a)^{(n)}(X -$$
a) ... (4)

In this formula, by interpolating data including a
high order term, a light beam intensity in the vicinity
of an evaluation point is approximated more precisely,
and an edge deviation quantity can be obtained with
high precision.

Similarly, an approximation formula of light beam
intensity in the vicinity of a certain evaluation point
(x = a) can be expressed by a polynomial of n-story
differentiation in the coordinate of x = a, and
approximation can be carried out by the following
Taylor expansion formula

$$f(x) = f(x = a) + f^{(1)}(x = a)(X - a)/1! + f^{(2)}(x =$$
$$a)/2!(X - a)^2 + \ldots + f^n(x = a)/n!*(X - a)^n \ldots (5)$$

Further, a inclination in a direction vertical to
an edge of an evaluation point has been obtained by
carrying out one-story differentiation. However,
a inclination in a tangent direction with regard to

an edge is further obtained and combined with the

inclination in the direction vertical to define

a inclination. Then, an edge deviation quantity can

be calculated from the obtained inclination and

5   a difference between light beam intensity at an

evaluation point and a reference exposure quantity.

Furthermore, in the embodiments, an edge deviation

quantity during the best focus in which an optical

image forms a focus on a wafer has been obtained.

10   However, a variety of de-focuses or an exposure

quantity creating a desired dimension can be set

without being limited to the best focus.

Moreover, the above embodiments have been

described, assuming that ultrasonic light of about 0.1

15   to 0.2 μm in wavelength is practically used or under

development. However, the present invention can be

applied even in a situation in which light having

a suitable short wavelength or X-ray is required with

high integrity, namely, with advancement of a finer

20   semiconductor pattern.

According to aspects of the present invention,

there can be provided a calculation method, a verifica-

tion method, a verification program, and a verification

system for an edge deviation quantity capable of

25   significantly reducing and calculating a calculation

load at a high speed in calculation of light beam

intensity, and a semiconductor manufacturing method.